

# OpcStateMachineNode Members

**Namespace:** Opc.UaFx

**Assemblies:** Opc.UaFx.Advanced.dll, Opc.UaFx.Advanced.dll

The [OpcStateMachineNode](#) type exposes the following members.

## Constructors

### OpcStateMachineNode(IOpcNode, OpcName)

Initializes a new instance of the [OpcStateMachineNode](#) class accessible by the **name** specified as a child node of the **parent** node given.

**C#**

```
public OpcStateMachineNode(IOpcNode parent, OpcName name)
```

#### Parameters

**parent** [IOpcNode](#)

The [IOpcNode](#) used as the parent node or a null reference (Nothing in Visual Basic) in the case there is no parent node available.

**name** [OpcName](#)

The [OpcName](#) through that the new state machine node can be accessed.

### OpcStateMachineNode(IOpcNode, OpcName, OpcNodeId)

Initializes a new instance of the [OpcStateMachineNode](#) class accessible by the **name** and **id** specified as a child node of the **parent** node given.

**C#**

```
public OpcStateMachineNode(IOpcNode parent, OpcName name, OpcNodeId id)
```

#### Parameters

**parent** [IOpcNode](#)

The [IOpcNode](#) used as the parent node or a null reference (Nothing in Visual Basic) in the case there is no parent node available.

**name** [OpcName](#)

The [OpcName](#) through that the new state machine node can be accessed.

**id** [OpcNodeId](#)

The [OpcNodeId](#) through that the new state machine node can be identified and accessed.

## OpcStateMachineNode(OpcName)

Initializes a new instance of the [OpcStateMachineNode](#) class accessible by the **name** specified.

**C#**

```
public OpcStateMachineNode(OpcName name)
```

### Parameters

**name** [OpcName](#)

The [OpcName](#) through that the new state machine node can be accessed.

## OpcStateMachineNode(OpcName, OpcNodeId)

Initializes a new instance of the [OpcStateMachineNode](#) class accessible by the **name** and **id** specified.

**C#**

```
public OpcStateMachineNode(OpcName name, OpcNodeId id)
```

### Parameters

**name** [OpcName](#)

The [OpcName](#) through that the new state machine node can be accessed.

**id** [OpcNodeId](#)

The [OpcNodeId](#) through that the new state machine node can be identified and accessed.

## Properties

### CurrentState

Gets or sets the current state of the [OpcStateMachineNode](#) and provides a human readable name for the current state which may not be suitable for use in application control logic. Applications should use the [VariableId](#) property of the [CurrentStateNode](#) if they need a unique identifier for the state.

**C#**

```
public virtual OpcText CurrentState { get; set; }
```

### Property Value

[OpcText](#)

A human readable name for the current state which may not be suitable for use in application control logic.

# CurrentStateNode

Gets the [OpcStateVariableNode](#) of the [CurrentState](#) property.

**C#**

```
public OpcStateVariableNode CurrentStateNode { get; }
```

## Property Value

[OpcStateVariableNode](#)

An instance of the [OpcStateVariableNode](#) class.

# DefaultTypeDefinitionId

Gets the default identifier which identifies the node that defines the underlying node type from that this [OpcInstanceNode](#) has been created.

**C#**

```
protected override OpcNodeId DefaultTypeDefinitionId { get; }
```

## Property Value

[OpcNodeId](#)

The [OpcNodeId](#) of the type node from that this [OpcInstanceNode](#) has been created from. These type node defines the typical structure of an instance node of its type definition. If there exists no specific type definition node a null reference (Nothing in Visual Basic).

# LastTransition

Gets or sets the last transition which occurred in an instance and provides a human readable name for the last transition which may not be suitable for use in application control logic. Applications should use the [VariableId](#) property of the [LastTransitionNode](#) if they need a unique identifier for the transition.

**C#**

```
public virtual OpcText LastTransition { get; set; }
```

## Property Value

[OpcText](#)

A human readable name for the last transition which may not be suitable for use in application control logic.

# LastTransitionNode

Gets the [OpcTransitionVariableNode](#) of the [LastTransition](#) property.

## C#

```
public OpcTransitionVariableNode LastTransitionNode { get; }
```

## Property Value

[OpcTransitionVariableNode](#)

An instance of the [OpcTransitionVariableNode](#) class.

# Table of Contents

|   |   |
|---|---|
| <b>Constructors</b>                               | 1 |
| OpcStateMachineNode(IOpcNode, OpcName)            | 1 |
| OpcStateMachineNode(IOpcNode, OpcName, OpcNodeId) | 1 |
| OpcStateMachineNode(OpcName)                      | 2 |
| OpcStateMachineNode(OpcName, OpcNodeId)           | 2 |
| <b>Properties</b>                                 | 2 |
| CurrentState                                      | 2 |
| CurrentStateNode                                  | 3 |
| DefaultTypeDefinitionId                           | 3 |
| LastTransition                                    | 3 |
| LastTransitionNode                                | 4 |

