

# PlcByteArrayInfo Members

**Namespace:** IPS7Lnk.Advanced

**Assemblies:** IPS7LnkNet.Advanced.dll, IPS7LnkNet.Advanced.dll

The [PlcByteArrayInfo](#) type exposes the following members.

## Constructors

### PlcByteArrayInfo(PlcByteArrayType, PlcName)

Initializes a new instance of the [PlcByteArrayInfo](#) class using the specified **type** and **name**.

**C#**

```
public PlcByteArrayInfo(PlcByteArrayType type, PlcName name)
```

#### Parameters

**type** [PlcByteArrayType](#)

The type of array member.

**name** [PlcName](#)

The name of the array member.

#### Exceptions

[ArgumentException](#)

The **type** is not a one dimensional array type.

[ArgumentNullException](#)

The **type** or **name** is a null reference (Nothing in Visual Basic).

### PlcByteArrayInfo(PlcIdentity, PlcName, Int32)

Initializes a new instance of the [PlcByteArrayInfo](#) class using the specified **identity**, **name** and **length**.

**C#**

```
public PlcByteArrayInfo(PlcIdentity identity, PlcName name, int length)
```

#### Parameters

**identity** [PlcIdentity](#)

The [PlcIdentity](#) of the type of array member.

**name** [PlcName](#)

The name of the array member.

**length** Int32

The length of the array member.

## Exceptions

[ArgumentException](#)

The **identity** does not refer to the [Byte](#).

[ArgumentNullException](#)

The **identity**, **name** is a null reference (Nothing in Visual Basic).

[ArgumentOutOfRangeException](#)

The **length** is out of the bounds defined by [MinLength](#) and [MaxLength](#).

## PlcByteArrayInfo(PlcName, Int32)

Initializes a new instance of the [PlcByteArrayInfo](#) class using the specified **name** and **length**.

### C#

```
public PlcByteArrayInfo(PlcName name, int length)
```

## Parameters

**name** PlcName

The name of the array member.

**length** Int32

The length of the array member.

## Exceptions

[ArgumentNullException](#)

The **name** is a null reference (Nothing in Visual Basic).

[ArgumentOutOfRangeException](#)

The **length** is out of the bounds defined by [MinLength](#) and [MaxLength](#).

## Methods

### MakeAbsoluteMember(PlcIdentity)

Retrieves the [PlcByteArrayInfo](#) as an absolute addressable PLC data member.

## C#

```
public override IPlcMemberInfo MakeAbsoluteMember(PlcIdentity identity)
```

### Parameters

**identity** PlcIdentity

The **PlcIdentity** to use to define the absolute location. This identity is used to define the basis starting from that the member is be located.

### Returns

**IPlcMemberInfo**

In case there **IsAbsolute** is equals true the reference to this member; otherwise a new instance of the member which refers to an absolute **PlcType**.

### Exceptions

**ArgumentException**

The **identity** specified does not provide the necessary information required to address the type of data.

**ArgumentNullException**

The **identity** is a null reference (Nothing in Visual Basic).

## RelocateCore(PlcType)

Relocates the member to the **type** specified.

## C#

```
protected override IPlcMemberInfo RelocateCore(PlcType type)
```

### Parameters

**type** PlcType

The **PlcType** to that the member is to be relocated.

### Returns

**IPlcMemberInfo**

A new instance of the same type as this PLC member instance relocated to the **type** specified.



# Table of Contents

<b>Constructors</b> .....	1
PlcByteArrayInfo(PlcByteArrayType, PlcName) .....	1
PlcByteArrayInfo(PlcIdentity, PlcName, Int32) .....	1
PlcByteArrayInfo(PlcName, Int32) .....	2
<b>Methods</b> .....	2
MakeAbsoluteMember(PlcIdentity) .....	2
RelocateCore(PlcType) .....	3